

Installation and Operation Manual



FlexPhones Master

Manual Update: 06/25/2013

Due to the dynamic nature of product design, the information contained in this document is subject to change without notice. Broadcast Tools, Inc., assumes no responsibility for errors and/or omissions contained in this document. Revisions of this information or new editions may be issued to incorporate such changes.


*Broadcast Tools® is a registered trademark of Broadcast Tools, Inc.
Copyright, 1989 - 2013 by Broadcast Tools, Inc. All rights reserved.
No part of this document may be reproduced or distributed without permission.*

Visit www.broadcasttools.com for important product update information.

Table of Contents

Section Title	Page #
Introduction	3
Safety Information	3
Who to Contact for Help	3
Product Description	4
Additional Features	4
Installation	5
Operation	8
Specifications	9
Warranty	10
Functional Diagram	Appendix
Schematic and Component Layout	Appendix
Jumper Layout	Appendix
Installation Example	Appendix

WEBSITE:
Visit our web site for product updates and additional information.



INTRODUCTION

Thank you for your purchase of a Broadcast Tools® **FlexPhones Master** multi-user headphone system (referred to as the FlexPhones Master or Master throughout this manual). We're confident that this product will give you many years of dependable service. This manual is intended to give you all the information needed to install and operate the Broadcast Tools® FlexPhones Master.

SAFETY INFORMATION

Only qualified personnel should install Broadcast Tools® products. Incorrect or inappropriate use and/or installation could result in a hazardous condition.

Broadcast Tools, Inc., is unable to support NON-Broadcast Tools software, hardware or NON-Broadcast Tools computer/hardware/software problems. If you experience these problems, please research your hardware/software instruction manuals or contact the manufacturers technical support department.

WHO TO CONTACT FOR HELP

If you have any questions regarding your product or you need assistance, please contact your distributor from whom you purchased this equipment.

If you would like more information about Broadcast Tools® products, you may reach us at:

Broadcast Tools, Inc.

131 State Street
Sedro-Woolley, WA 98284-1540 USA
Voice: 360 . 854 . 9559
Fax: 866 . 783 . 1742
Internet Home Page: www.broadcasttools.com
E-mail: support@broadcasttools.com

**THANK YOU FOR CHOOSING
BROADCAST TOOLS® BRAND PRODUCTS!**

Broadcast Tools is a Veteran Owned Business



Designed, Assembled and Supported in WA State, USA



CAUTION!

Broadcast Tools® Products, as with any electronic device, can fail without warning. Do not use this product in applications where a life threatening condition could result due to failure.




NOTE:

This manual should be read thoroughly before installation and operation.

WEBSITE:

Visit our web site for product updates and additional information.



Product Description:

The FlexPhones Master is a professional Broadcast/Studio six channel distributed headphone system with independent talkback capabilities. Each of the six channels provides stereo program monitoring and selective talkback with interconnection via CAT5 cable to multiple Active Headphone Remotes (AHR-1) and/or the Monitor Selector Interface (MSI). Multiple masters may be cascaded to form larger systems. The FlexPhones Master is equipped with inputs for stereo program and talkback audio. Rear panel program and talkback trimmers are provided to pre-set maximum input levels. The microphone/line level talkback input is available via a rear panel plug-in euroblock connector, while the front panel XLR connector facilitates the use of a user provided gooseneck microphone or headset. The front panel is equipped with a level control for local headphones with both 1/4" and 1/8" stereo headphone jacks. The six front panel talkback switches allow the user to independently communicate with each AHR-1 listener and can be configured to insert talkback audio into only the left or both ears and dim either or both program channels. Any combination of switches may be pressed, while the "All-Call" interrupts all listeners. The Talkback function can be remotely controlled. Six RJ45 jacks are provided to distribute audio and power via CAT5 cable to the AHR-1's, and/or MSI's that conform to the StudioHub+ wiring format. Low-Z balanced audio distribution is used to preclude audio degradation with long cable runs.


Additional features include:

Front panel power and talkback LED indicators, surge protected internal bipolar 24/15-vdc-power supply affording superior headroom and high definition audio. The optional Monitor Selector Interface (MSI) provides transparent audio switching of the program and talkback functions into a studio's monitor system. The MSI is inserted between a studio's air or console's monitor feed and monitor amplifier. The MSI may be connected to the FlexPhones Master or AHR-1. All audio connections are balanced and supplied on plug-in euroblock screw terminals.

The FlexPhones Master half rack profile, allows the unit to be set on a desktop, mounted on a wall or the RA-1, Rack-Able mounting shelf. The AHR-1 may be desktop mounted, under counter or with the optional HR-1/MP or HR-1/MP-XLR mounting plates, which may be turret mounted.

WEBSITE:

Visit our web site for product updates and additional information.



DESCRIPTION

Installation:

Please examine your FlexPhones Master and/or AHR-1 carefully for any damage that may have been sustained during shipping. If any is noted, please notify the shipper immediately and retain the packaging for inspection by the shipper. The package should contain the FlexPhones Master, 16vac@600ma wall power transformer, two CAT5 cables and this manual.

Installation of the FlexPhones Master in high RF environments should be performed with care. Shielded cable is suggested for all audio connections.

All shields should be tied to the EGND terminals. The station ground should be connected to the chassis ground screw located on the far right side of the FlexPhones Master as viewed from the rear. It is recommended that all cables connected to the FlexPhones Master be looped through ferrite cores to suppress RF. Surge protection with RF filtering is also suggested for the wall transformer. The purchase of an inexpensive UPS will provide back up in case of power outages.

Connections are via plug-in euroblock connectors and RJ45 connectors. Remove the connector from the header; remove about 1/8" of insulation from each wire. Insert the wire into the desired terminal and then tighten the screw. Be sure no bare wires are exposed. Reinstall the connectors.

Stereo Program Input

Normal program audio should be connected to the + and - inputs for balanced operation, or to the + input and grounding the - side for unbalanced input operation on TB1 (bottom). Audio levels should be between -15 and +4dBu.

Talkback Audio Input

Mic or line level audio should be connected to the + and - inputs for balanced operation, or to the + input and grounding the - side for unbalanced input operation on either TB1 (top) or the front panel XLR connector. Audio levels should be between -60 and -30dBu in MIC position or -15 and +4dBu in LINE position. JP1 and JP2 are used to set the talkback input for either MIC or LINE levels. Follow the jumper layout in the appendix to set these two jumpers to the desired position. The factory default is set to MIC.

Talkback Audio Output

The unbalanced output can be used to feed additional FlexPhones Master talkback inputs. Connections to TB1 (top) can be made to the + output and ground for unbalanced output operation.




NOTE:

For proper installation, follow the silkscreen labels on the rear panel.

WEBSITE:

Visit our web site for product updates and additional information.



DIM jumper configuration

Removing either or both of the Dim jumpers mutes the program audio during a talkback session, while inserting either or both will dim the program audio approximately 20db below normal program levels. Use the table below along with the jumper layout sheet in the appendix to properly configure. Factory defaults have these jumpers installed.

Right ear talkback enable jumper:

In a talkback session, talkback audio is always feed into the left ear. Placing a jumper over the desired header will enable talkback audio in the right ear. Use the table below along with the jumper layout sheet in the appendix to properly configure. Factory default has these jumpers installed.

Function	Chnl 1	Chnl 2	Chnl 3	Chnl 4	Chnl 5	Chnl 6
LT Dim	JP5	JP8	JP11	JP14	JP17	JP20
RT Dim	JP6	JP9	JP12	JP15	JP18	JP21
RT T/B Enable	JP7	JP10	JP13	JP16	JP19	JP22

Auxiliary Remote/Local jumper set-up

We provide the wire attached to pin 5 of each RJ45 for use by the user. The wire terminates on a three-position header. The header is labeled JPxx. The factory default is set to Remote. Use the table below along with the jumper layout sheet in the appendix to properly configure.

Function	RMT 1	RMT 2	RMT 3	RMT 4	RMT 5	RMT 6
	JP24	JP26	JP28	JP30	JP32	JP34
Remote	1 & 2	1 & 2	1 & 2	1 & 2	1 & 2	1 & 2
Local	2 & 3	2 & 3	2 & 3	2 & 3	2 & 3	2 & 3

Remote Control input jumper set-up


Each optically isolated input is equipped with a four-position header. The header is labeled JPxx. The factory default is set for a DRY (5 vdc source) input (switch, contact, open collector) with a jumper between 1 & 2 and another jumper over 3 & 4. To change the input to WET (user supplied voltage between 5 and 24vdc), remove both jumpers and place ONE jumper over pins 2 & 3. Use the table below along with the jumper layout sheet in the appendix to properly configure.

! NOTE: Refer to the schematic diagram for the proper polarity when attaching equipment to each input.

Function	RMT 1	RMT 2	RMT 3	RMT 4	RMT 5	RMT 6	All-Call
	JP23	JP25	JP27	JP29	JP31	JP33	JP35
Wet 2 & 3	A = Anode B = Cath	A = Anode B = Cath	A = Anode B = Cath	A = Anode B = Cath	A = Anode B = Cath	A = Anode B = Cath	A = Anode B = Cath
Dry 1 & 2 / 3 & 4	A = Gnd B = Cath	A = Gnd B = Cath	A = Gnd B = Cath	A = Gnd B = Cath	A = Gnd B = Cath	A = Gnd B = Cath	A = Gnd B = Cath

WEBSITE:

Visit our web site for product updates and additional information.



INSTALLATION

Cable Interconnection

After completion of the jumper set-up and the audio connections have been made, connection of the CAT5 cable can be started. Connect the user supplied CAT5 cable between the desired channels (follow the numbers on the chassis) rear panel RJ45 on the FlexPhones Master and each AHR-1 and/or MSI. Up to two AHR-1's or one AHR-1 and one MSI can be daisy-chained from each RJ45 on the Master.

Program Level Setup

Turn the rear panel "Master Pgm Lvl" trimmer CCW. Set all headphone level controls to 1 o'clock. Plug a set of headphones in to either of the AHR-1's headphone jacks. Feed the desired program level into the Master and adjust R2 the rear panel "Master Pgm Lvl" trimmer for the desired level. This also holds true for the MSI.

Talkback Level Setup

Turn the rear panel "T/B Lvl" trimmer CCW. Plug a set of headphones in to either of the AHR-1's headphone jacks. Hold down the talkback channel button that the AHR-1 is connected to and adjust the "T/B Lvl" trimmer R21 on the rear panel of the master for the appropriate talkback level. Depending on the configuration for each channel, the program audio will be muted or dimmed in each ear, while the talkback will be present on either or both ears. This also holds true for the MSI.

Microphone Phantom Power Jumper

To power microphones needing phantom power; install the supplied jumper over JP36. JP36 is supplied but not installed. 15vdc is supplied when installed.

Operation:

To call any combination of AHR-1's press the desired front panel talkback button(s) or the ALL CALL button. You may also do the same using user supplied momentary normally open dry contact switches connected across each of the rear panel remote control inputs.


The Front panel headphone jacks and level control only monitor program. Only one set of headphones should be used.

NOTE: *The talkback feature may be added by reconfiguring internal jumpers. Consult the factory before making this change.*

NOTE: *8 ohm and/or monaural headphones should not be used with these products.*

WEBSITE:


Visit our web site for product updates and additional information.



Specifications:

Program Input Level	-15 to +4 dBu. MIL+24dBu, balanced, bridging 10k Ω .
Talkback Input Level	-60 to -30 dBu MIC / -15 to +4dBu LINE, balanced. Microphone phantom power +15vdc.
Gain	6 dB.
Frequency Response	10 to 20 kHz; +/- .025dB
Signal/Noise Ratio	>85 dB nominal, weighted 10 to 22Khz.
Distortion	0.005% THD, nominal.
IMD (250/7kHz)	0.005% IMD, nominal.
Headphone Output	24 to 600 W headphones. 200mw nominal.
Switching Method	Professional level analog switch arrays.
Logic	CMOS.
Operation Control	Front Panel - Momentary switches. Remote - Optically isolated (5 to 24vdc) wet or dry. Default = Dry (5 volt internally sourced)
Status/Control	Front Panel - LED indicators.
Interfacing	Master audio & remote rontrol - Rear panel euroblock removable screw terminals with mating connectors and female XLR. AHR-1 power, audio and control - RJ45 connectors and plug-in euroblock screw terminals. MSI power, audio and control - RJ45 connectors and plug-in euroblock screw terminals. Wiring conforms to the StudioHub+ format.
Power	16 Vac @ 600 ma, 120 Vac 50-60 Hz power transformer. Supplied. (CE 240 Vac 50-60 Hz optional)
Mechanical	Master - 8.50" x 1.55" x 6.00" (WHD) / Weight: 3.0 lbs. AHR-1 – 3.70" x 1.55" x 3.50" (WHD) / Weight: 1.0 lbs
Options	Master - RA-1, 1 RU rack Shelf. Hold two units. AHR-1 - HR-1/MP, mounting panel AHR-1 - HR-1/MP-XLR, mounting plate with XLR connector hole. MSI, Monitor Selector Interface.

WEBSITE:
Visit our web site for product updates and additional information.



LIMITED WARRANTY

The term “Buyer” as used in this document refers to and includes both (but only) (a) any person or entity who acquires such an item for the purpose of resale to others (i.e., a dealer or distributor of an item), and (b) the first person or entity who acquires such an item for such person’s or entity’s own use.

Broadcast Tools warrants to each Buyer of any item manufactured by Broadcast Tools that the item will be free from defects in materials and workmanship at the time it is shipped by Broadcast Tools if the item is properly installed, used and maintained.

EXCLUSIVE REMEDIES

If Broadcast Tools is notified, in writing, of a failure of any item manufactured by Broadcast Tools to conform to the foregoing Limited Warranty within one (1) year following the date of the Buyer’s acquisition of the item, and if the item is returned to Broadcast Tools in accordance with Broadcast Tools’ instructions for confirmation by inspection of the defect (which at Broadcast Tools’ election may include, without limitation, a requirement that the Buyer first obtain a Return Authorization number from Broadcast Tools, that the Buyer furnish proof of purchase in the form of an invoice and/or receipt, and that the Buyer prepay all freight charges associated with any return of the item to Broadcast Tools using such freight service as Broadcast Tools reasonably may specify), Broadcast Tools will repair or replace the defective item, or will refund the purchase price paid by the Buyer for the item. Broadcast Tools shall have the exclusive right to choose between these alternative remedies.

NO OTHER WARRANTIES OR REMEDIES

TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, BROADCAST TOOLS AND ITS SUPPLIERS DISCLAIM ALL OTHER WARRANTIES, EITHER EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE; AND THE FOREGOING ALTERNATIVE REMEDIES SHALL BE EXCLUSIVE OF ALL OTHER REMEDIES. THIS LIMITED WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS. YOU MAY HAVE OTHER RIGHTS, WHICH VARY FROM STATE/JURISDICTION TO STATE/JURISDICTION.

NO LIABILITY FOR CONSEQUENTIAL DAMAGES


TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, NEITHER BROADCAST TOOLS NOR ANY OF ITS SUPPLIERS SHALL HAVE ANY LIABILITY FOR ANY SPECIAL, INCIDENTAL, INDIRECT, CONSEQUENTIAL OR PUNITIVE DAMAGES WHATSOEVER (INCLUDING, WITHOUT LIMITATION, ANY DAMAGES FOR LOST PROFITS, BUSINESS INTERRUPTION, LOSS OF DATA OR INFORMATION, COST OF CAPITAL, CLAIMS OF CUSTOMERS, OR ANY OTHER PECUNIARY LOSS) ARISING OUT OF THE USE OF OR THE INABILITY TO USE ANY ITEM SUPPLIED BY BROADCAST TOOLS, EVEN IF BROADCAST TOOLS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES HAVE ANY LIABILITY FOR ANY SPECIAL, INCIDENTAL, CONSEQUENTIAL, EXEMPLARY OR PUNITIVE DAMAGES. THIS LIMITATION OF LIABILITY APPLIES WHETHER A CLAIM IS ONE ALLEGING BREACH OF A CONTRACT OR WARRANTY, NEGLIGENCE OR OTHER TORT, FOR THE VIOLATION OF ANY STATUTORY DUTY, THE FAILURE OF ANY LIMITED OR EXCLUSIVE REMEDY TO ACHIEVE ITS ESSENTIAL PURPOSE, OR ANY OTHER CLAIM OF ANY NATURE. BECAUSE SOME STATES AND JURISDICTIONS DO NOT ALLOW THE EXCLUSION OR LIMITATION OF LIABILITY FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES, THIS LIMITATION MAY NOT APPLY TO YOU.

Broadcast Tools, Inc.




131 State Street
Sedro-Woolley, WA 98284 • USA

360.854.9559 **voice** • 866.783.1742 **fax**
support@broadcasttools.com **e-mail**
www.broadcasttools.com **website**

Functional Diagram




* Must be purchased separately.




Copyright © 2006 Broadcast Tools, Inc. All rights reserved. This document is the property of Broadcast Tools, Inc. and shall not be used or reproduced in any form without the written permission of Broadcast Tools, Inc. No copies shall be made of it and all proprietary rights in it are the property of Broadcast Tools, Inc.

Company	BROADCAST TOOLS, INC.
Title	FLEX PHONES MASTER
Size	Document Number: FPMCL.SCH
Rev	B
Date	JULY 24, 2006 Sheet 1 of 5




THIS INFORMATION IS THE PROPERTY OF Broadcast Tools, Inc. and shall not be used except with the written permission of Broadcast Tools, Inc. no copies shall be made of it and all proprietary rights in this document shall remain the property of Broadcast Tools, Inc.

BROADCAST TOOLS, INC.	
Title	FLEX PHONES MASTER
Size	Document Number: FPM02.SCH
Date:	JULY 24, 2006 Sheet 2 of 5
REV	C




THIS INFORMATION IS THE PROPERTY OF
Broadcast Tools, Inc. and shall not be used
except with the written permission of
Broadcast Tools, Inc. No copies shall be
made of it and all proprietary rights in
it are reserved. This document and its contents
are the property of Broadcast Tools, Inc.

BROADCAST TOOLS, INC.	
Title	FLEX PHONES MASTER
Size	Document Number: FPM3.SCH
Date:	JULY 24, 2006 Sheet 3 of 5
REV	C




...the property of
Broadcast Tools, Inc. and shall not be used
except with the written permission of
Broadcast Tools, Inc. No copies shall be
made of this document or its contents. All
rights reserved. This information shall be
the property of Broadcast Tools, Inc.

BROADCAST TOOLS, INC.	
Title	FLEX PHONES MASTER
Size	Document Number FPM04.SCH
REV	B
Date:	JULY 24, 2006/Sheet 4 of 5




BROADCAST TOOLS, INC.	
Title	FLEX PHONES MASTER
Size	Document Number FPM05.SCH
REV	C
Date:	JULY 24, 2006 Sheet 5 of 5



THIS INFORMATION IS THE PROPERTY OF Broadcast Tools, Inc. and shall not be used except with the written permission of Broadcast Tools, Inc. No copies shall be made of this program file or schematic are the property of Broadcast Tools, Inc.

Broadcast Tools, Inc.	
Title	AHR-1
Size	Document Number AHR1A1.SCH
REV	B
Date:	June 27, 2006
Sheet	1 of 1




THIS INFORMATION IS THE PROPERTY OF Broadcast Tools, Inc. and shall not be used except with the written permission of Broadcast Tools, Inc.; no copies shall be made of it and all proprietary rights in it shall remain the property of Broadcast Tools, Inc.

Title	Broadcast Tools, Inc.
Size	AHR-1
Document Number	AHR1D1.SCH
Date	June 16, 2008
Sheet	1 of 1
REV	D

Broadcast Tools® FlexPhones Master

Jumper Layout





Appendix

Broadcast Tools® AHR-1 and AHR-1 Plus

Headphone Remote


Up to six AHR-1 or AHR-1 Plus units may be connected to a FlexPhones Master.



Flush mount into furniture (w/ AHR-1 and AHR-1 Plus/MP-XLR option). Connector not included. XLR hole compatible with the Switchcraft D3F and Neutrik NC3FP-1 connectors.



Flush mount into furniture (w/ AHR-1 and AHR-1 Plus/MP option).



Mount to top or underside of desk or cabinet.

BROADCAST
tools
tinyTOOLS
POWERED BY BROADCASTtools®
Sentinel® TOOLS

BROADCAST
tools
tinyTOOLS
POWERED BY BROADCASTtools®
Sentinel® TOOLS

BROADCAST
tools
tinyTOOLS
POWERED BY BROADCASTtools®
Sentinel® TOOLS

131 State Street, Sedro-Woolley, WA 98284 • 360.854.9559 • Fax 866.783.1742

Visit us online at www.broadcasttools.com
Copyright © 1989-2013 by Broadcast Tools, Inc. All Rights Reserved.